CLOCK SKEW TOLERANT CLOCKING SCHEME

EDGARDO F. KLASS

FIELD OF THE INVENTION

5

The present invention relates generally to logic
circuits and, more particularly, to a skew tolerant
clocking scheme for combinational logic circuits.

10 ## BACKGROUND OF THE INVENTION

FIG.1 shows a typical single-phase latch design
100 including: a sending latch 101; a receiving latch
103 and combinational logic 105 coupled between sending
15 latch 101 and receiving latch 103.

As shown in FIG.1, sending latch 101 includes:
clock input 115 for receiving a clock signal CLK; first
D terminal 107 and data signal D1; second D terminal
109 and data signal D2; first Q terminal 111 and signal
20 Q1; and second Q terminal 113 and signal Q2. Likewise,
receiving latch 103 includes: clock input 125 for
receiving clock signal CLK; first D terminal 127 and
data signal D1'; second D terminal 129 and data signal
D2'; first Q terminal 121 and signal Q1'; and second Q
25 terminal 123 and signal Q2'. .

Also shown in FIG.1 are two paths, max path 131
and min path 141, through combinational logic 105.
Those of skill in the art will readily recognize that
while in FIG.1 max path 131 and min path 141 are shown
30 as independent, in practice max path 131 and min path
141 are not necessarily independent paths, i.e., max
path 131 and min path 141 can converge, diverge or
intersect. However, for simplicity of illustration
they are shown in FIG.1, and assumed in the following
35 discussion, to be independent paths.

When latches are used as synchronization elements,
for instance when latches are used to separate pipeline
stages, there are two important timing constraints that
must be taken into account. The first is the potential
40 presence of slow-propagating signals, such as signals

through max-path 131 in FIG.1, which determines the
maximum speed at which the system can be clocked. The
second is the potential presence of fast propagating
signals, such as signals through min-path 141 in FIG.1
and determines race conditions.

The max-timing problem can be expressed as:

1.Given the maximum propagation delay, i.e., max-
path 131, within a pipeline stage, what is the maximum
clock frequency the circuit can accommodate? or

2. Given a fixed clock frequency, what is the
maximum allowed propagation delay within a stage?

The min-timing problem, also known as "race
through" or a "race condition" occurs where the clock
signal races ahead of the data stream. The min-time
problem typically arises when an early arriving clock
sends data through a short, or minimal, logic path,
such as min-path 141 in FIG.1, and this causes the next
stage to update before the destination clock samples
the previous data. The same result occurs if the
destination clock is late. The result is data racing
through two or more stages in a single clock cycle.
This is a functional, and typically non-recoverable,
problem. The min-time problem is particularly
problematic because the min-time problem is not related
to the clock cycle, i.e., is frequency independent and
therefore, in the prior art, could not be fixed by
adjusting the clock frequency, as could be done to
solve the max-time problem.

FIG.2 shows the typical single-phase latch design
100 of FIG.1 and three clock signals: normal clock
signal CLK 201 and skewed clock signals CLKe 203 and
CLKl 205. As shown in FIG.2 clock, signal CLKe is
early or "skewed" early with respect to clock signal
CLK by skew time Tskew 221 and clock signal CLKl is
late or "skewed" late with respect to clock signal CLK
by skew time Tskew 231.

Clock skew has become an ever-increasing problem as clock frequencies have continued to increase in microprocessor design since the higher the frequency of the clock, the larger percentage of the clock cycle is consumed by a given clock skew. Consequently, clock skew plays an important role with respect to the max-time and min-time problems discussed above.

FIG. 3 shows a signal diagram 300 for a typical synchronous design when operating as designed and when operating under conditions of early clock skew. Shown is the data signal 311 to be sampled including data packets 313, 315 and 317. It is important to note that data stream 311 changes value at points 308, 310, and 312 such that the data value in data packet 313 can be, and often is, different form the data value in data packet 315 or 317, i.e., the data value changes state from data packet 313 to data packet 315 and to data packet 317.

Also shown in FIG.3 is clock signal CLK 201. As is typical in the present state of the art, signal diagram 300 is for an "edge triggered" system wherein data stream 311 is sampled at the leading edges 324, 326, and 328 of the clock pulses 323, 325 and 327, respectively. Consequently, at time T1 301, leading edge 324 of pulse 323 of clock signal CLK 201 causes data to be sampled at point 314 of data packet 313 of data stream 311. Likewise, at time T2 303, leading edge 326 of pulse 325 of clock signal CLK 201 causes data to be sampled at point 316 of data packet 315 of data stream 311. Likewise, at time T3 305, leading edge 328 of pulse 327 of clock signal CLK 201 causes data to be sampled at point 318 of data packet 315 of data stream 311.

As shown in FIG.3, when the CLK signal is normal, i.e., clock signal 201, the operation the design is correct and in accordance with design goals since leading edge 324 of pulse 323 samples or reads data

-3-

packet 313, leading edge 326 of pulse 325 samples or
reads data packet 315, and leading edge 328 of pulse
327 samples or reads data packet 317. As long as this
is case, and data stream 311 remains synchronous with
clock signal CLK 201, the system functions correctly,
and the correct data is sampled at the correct time.

However, also shown in FIG.3 is early skewed clock
signal CLKe 203. In this instance the combination of
the max-time problem and the early clock skew 350
reduces the maximum clocking frequency in a prior art
design. As shown in FIG.3 skewed clock signal CLKe 203
differs from clock signal CLK 201 in that a leading or
"trigger" edge 354 of clock pulse 353 is displaced or
"skewed" early, or to the left, with respect to leading
edge 324 of clock pulse 323 by skew time 350.
Likewise, a leading "trigger" edge 326 of clock pulse
355 is displaced or "skewed" to the left with respect
to leading edge 326 of clock pulse 325 by skew time
350. Likewise, a leading "trigger" edge 358 of clock
pulse 357 is displaced or "skewed" to the left with
respect to leading edge 328 of clock pulse 327 by skew
time 350.

The max-time problem arises from the fact that
because of skew time 350, leading edge 354 of clock
pulse 353 of skewed clock signal CLKe 203 causes data
stream 311 to be sampled at time T4 307, and point 364
of data packet 302 instead of time T1 301, and point
314 of data packet 313. Consequently, data packet 302
is sampled incorrectly instead of the correct data
packet 313. Therefore, since the value of data packet
302 can be, and often is, different from the value of
data packet 313, incorrect data is sampled and used.

Likewise, because of skew time 350, leading edge
356 of clock pulse 355 of skewed clock signal CLKe 203
causes data stream 311 to be sampled at time T5 308,
and point 366 of data packet 313 instead of time T2
303, and point 316 of data packet 315. Consequently,

-4-

data packet 313 is sampled incorrectly instead of the correct data packet 315. Therefore, since the value of data packet 313 can be, and often is, different from the value of data packet 315, incorrect data is sampled

5   and used.

Finally, because of skew time 350, leading edge 358 of clock pulse 357 of skewed clock signal CLKe 203 causes data stream 311 to be sampled at time T6 309, and point 368 of data packet 315 instead of time T3

10 305, and point 318 of data packet 317. Consequently, data packet 315 is sampled incorrectly instead of the correct data packet 317. Therefore, since the value of data packet 315 can be, and often is, different from the value of data packet 317, incorrect data is sampled

15 and used.

Those of skill in the art will recognize that a similar problem exists for late clock skew such as the clock skew represented by clock signal 205 in FIG.2. However, in the case represented in FIG.3, the late

20 clock skew would have to be quite large to affect the data. However, those of skill in the art will recognize that the max-time problem discussed above is not strictly limited to early clock skew, that early clock skew was shown and discussed for illustrative

25 purposes only, and late clock skew could also have been shown for illustrative purposes with similar effect.

In the prior art, one solution for the max-time problem and clock skew problem was to simply slow down the clock signal 203 frequency to the point that

30 uncertainty in the clock arrival did not result in circuit failure. Obviously, slowing down the clock signal frequency had adverse effects on performance and was very undesirable.

Another prior art solution to the max-time problem

35 in latch-based designs was to employ "transparent" latches between stages. In this prior art solution, dual latches were typically employed that were operated

"or latched" by complementary clock phases as opposed to a clock leading edge. Consequently, the arrival of the clock was less critical and, when properly employed, a latch-based design could be made fairly

5   insensitive to the max-time problem. However, as discussed below, this prior art solution to the max-time time problem failed to address the other major problem, the min-time problem, and actually made the min-time problem even worse.

10   One other prior art solution to the max-time problem was the use of pulse latches with a very short transparency period determined by the clock pulse. Unlike flip-flop designs, pulse latch designs required only one latch and were relatively clock skew tolerant

15   for the max-time problem. However, pulse latches are extremely prone to the min-time problem discussed below because, in addition to the clock skew, the transparency period of the pulse latch also needed to be accounted for and designed to when determining

20   potential races.

The max-time problem is well know to those of skill in the art. Consequently, to avoid detracting from the present invention, a more detailed discussion of the max-time problem, and the effects of clock skew

25   on the max-time problem is omitted here. For a more detailed discussion of the max-time problem the reader is referred to virtually any computer engineering text book. For example, "THE COMPUTER ENGINEERING HANDBOOK", edited by Vojin G. Oklobdzija, CRC press

30   2002, ISBN 0-8493-0885-1, see chapter 10.2 "LATCHES AND FLIP-FLOPS", authored by the present inventor, pages 10-35 to 10-52.

As discussed above, the other major clock skew problem, the min-time or "race-through" problem, occurs

35   where the clock signal races ahead of the data stream in a flip-flop based design. The min-time typically arises when an early arriving clock sends data through

---

In addition, as also noted above, another prior art solution to the max-time problem in latch-based designs was to employ "transparent" latches between stages. In this prior art solution, dual latches were typically employed that were triggered by opposite clock phases. However, the addition of two latches per stage simply aggravated the min-time problem by adding additional opportunities for introduction of race through since race through could happen twice as often, i.e., once per each clock phase.

As also discussed above, one other prior art solution to the max-time problem was the use of pulse latches with a very short transparency period determined by the clock pulse. However, pulse latches are extremely prone to the min-time problem because, in addition to the clock skew, the transparency period of the pulse latch also needed to be accounted for and designed to when determining potential races.

What is needed is a clocking scheme that is clock skew tolerant for both max-time and min-time problems.

SUMMARY OF THE INVENTION

According to the present invention, a clock skew tolerant clocking scheme addresses both the max-time and min-time problems by using dual transparent pulsed latches operated by complementary phases of the clock signal.

According to the present invention, the first pulsed latch is triggered by a first pulse derived by the leading edge of a clock signal pulse and the second pulsed latch is triggered by a second pulse derived from the trailing edge of the clock signal. According to the present invention, the duration or pulse width of the first pulse and the second pulse is determined by the designer with longer, or larger, pulse widths

being more tolerant of the max-time problem and the shorter, or smaller, pulse widths being more tolerant of the min-time problem.

In one embodiment of the invention, the pulse width of the first and second pulses is designed to be ten to twenty-five percent of a clock cycle.

By employing transparent pulse latches, the clock skew tolerant clocking scheme of the invention provides max-time clock and using the present invention, the wider the transparent period is made, i.e., the larger the pulse width of the first and second pulses, the more clock skew max-time problem can be hidden. In addition, the wider the transparency period is made, the more well known time borrowing techniques can be employed. However, unlike the prior art latch based solutions to the max-time problem discussed above, the clock skew tolerant clocking scheme of the invention is also tolerant to min-time clocking skew problems as well. This is because, unlike prior art solutions, according to the invention, the transparency periods of the dual and complementary pulsed latches do not overlap and since the transparency periods of the dual and complementary pulsed latches are non-over-lapping, there is typically never a transparency period joining two successive pipeline stages and, therefore, there is no opportunity to introduce racing conditions.

In one embodiment of the invention, the pulse width of the first and second pulses is twenty percent of the clock cycle. Consequently, to a first order, the clock skew tolerant clocking scheme of the invention can tolerate thirty percent (fifty percent of a clock cycle minus the twenty percent pulse width) of clock cycle skew without a min-time failure.

In addition, since, according to the invention, the first pulsed latch is triggered by a first pulse derived by the leading edge of a clock signal pulse and the second pulsed latch is triggered by a second pulse

-9-

en

derived from the trailing edge of the clock signal, the min-time clock skew tolerance can be increased by changing the clock frequency since min-time skew tolerance, using the clock skew tolerant clocking scheme of the invention, is determined by the clock cycle time divided by twice the pulse width of either the first and second pulses. Consequently, unlike prior art schemes where the min-time problem was frequency independent, using the clock skew tolerant clocking scheme of the invention, both the max-time and the min-time problems can be solved by adjusting the clock frequency. This feature of the clock skew tolerant clocking scheme of the invention is particularly advantageous during the system debugging phase of the design process since padding and margining for min-time is not required using clock skew tolerant clocking scheme of the invention.

In addition, in one embodiment of the invention, the first and second pulses are generated locally by pulse generators and therefore, in one embodiment of the invention, the system remains a single-phase system and there is no need to distribute additional signals widely.

It is to be understood that both the foregoing general description and following detailed description are intended only to exemplify and explain the invention as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in, and constitute a part of this specification, illustrate embodiments of the invention and, together with the description, serve to explain the advantages and principles of the invention. In the drawings:

FIG.1 shows a typical single-phase latch design;

FIG.2 shows the typical single-phase latch design of FIG.1 and three clock signals, a normal clock signal CLK and skewed clock signals CLKe and CLKl.

FIG.3 shows a signal diagram for a typical synchronous data circuit design when operating as designed with little or no clock skew and where there is a max-time problem that reduces the maximum clocking frequency in a flip-flop based design;

FIG.4 shows one embodiment of the clock skew tolerant clocking scheme of the invention when employed with a typical synchronous data circuit design operating as designed, with little or no clock skew;

FIG.5 shows one embodiment of the clock skew tolerant clocking scheme of the invention when employed to solve a max-time problem;

FIG. 6 shows one embodiment of a dual transparent pulsed latches operated by complementary phases of the clock signal in accordance with one embodiment of the invention.

DETAILED DESCRIPTION

The invention will now be described in reference to the accompanying drawings. The same reference numbers may be used throughout the drawings and the following description to refer to the same or like parts.

According to the present invention, a clock skew tolerant clocking scheme (400 in FIG. 4 and 500 in FIG. 5) addresses both the max-time and min-time problem by using dual transparent pulsed latches (601, 603 in

FIG.6) operated by complementary phases of the clock
signal (201 in FIG.s 2 and 4 and 203 in FIG.s 2 and 5).

According to the present invention, the first
pulsed latch (601 in FIG.6) is triggered by a first
5   pulse (411, 413, and 415 in FIG. 4 and 511, 513 and 515
in FIG. 5) derived by the leading edge (324, 326, and
328 in FIG.s 3 and 4 and 354, 356 and 358 in FIG.s 3
and 5) of the clock signal pulse (323, 325, and 327 in
FIG.s 3 and 4 and 353, 355 and 357 in FIG.s 3 and 5)
10 and the second pulsed latch (603 in FIG.6) is triggered
by a second pulse (421, 423, and 425 in FIG.4 and 521,
523 and 525 in FIG.5) derived from the trailing edge
(474, 476, and 478 in FIG.4 and 574, 576 and 578 in
FIG.5) of the clock signal pulse (323, 325, and 327 in
15 FIG.s 3 and 4 and 353, 355 and 357 in FIG.s 3 and 5).
According to the present invention, the duration or
pulse width (405 in FIG.4 and 505 in FIG.5) of the
first pulse and the pulse width (407 in FIG.4 and 507
in FIG.5) of the second pulse is determined by the
20 designer with longer or larger pulse widths being more
tolerant of the max-time problem and the shorter or
smaller pulse width being more tolerant of the min-time
problem. In one embodiment of the invention, the pulse
width of the first and second pulses is designed to be
25 ten to twenty-five percent of a clock cycle.

By employing transparent latches, the clock skew
tolerant clocking scheme of the invention is max-time
clock skew tolerant and the wider the transparent
period is made, i.e., the larger the pulse width, the
30 more clock skew can be hidden. In addition, the wider
the transparency period is made, the more time
borrowing techniques can be employed. However, unlike
the prior art latch based solutions to the max-time
problem discussed above, the clock skew tolerant
35 clocking scheme of the invention is also tolerant to
min-time clocking skew problems as well. This is
because, unlike prior art solutions, according to the

invention, the transparency periods of the dual and complementary pulsed latches do not overlap and are separated by separation windows (481, 483, and 485 in FIG.4 and 581, 583, and 585 in FIG.5). Since the transparency periods of the dual and complementary pulsed latches are non-over-lapping, there is almost never a transparency period between two successive stages and, therefore, there is no opportunity to introduce racing conditions.

In one embodiment of the invention, the pulse width of the first and second pulses is twenty percent of the clock cycle. Consequently, to a first order, the clock skew tolerant clocking scheme of the invention can tolerate thirty percent (fifty percent of a clock cycle minus the twenty percent pulse width) of clock cycle skew without a min-time failure.

In addition, since, according to the invention, the first pulsed latch is triggered by a first pulse derived by the leading edge of the clock signal pulse and the second pulsed latch is triggered by a second pulse derived from the trailing edge of the clock signal, the min-time clock skew tolerance can be increased by changing the clock frequency since min-time skew tolerance, using the clock skew tolerant clocking scheme of the invention is determined by the clock cycle time divided by twice the pulse width of either the first and second pulses. Consequently, unlike prior art schemes where the min-time problem was frequency independent, using the clock skew tolerant clocking scheme of the invention, both the max-time and the min-time problems can be solved by adjusting the clock frequency. This feature of the clock skew tolerant clocking scheme of the invention is particularly advantageous during the system debugging phase of the design process since padding and margining for min-time is not required using clock skew tolerant clocking scheme of the invention.

FIG. 4 shows one embodiment of the clock skew tolerant clocking scheme 400 of the invention when employed with a typical synchronous data circuit design operating as designed, with little or no clock skew, such as the situation depicted in FIG.3 and discussed above.

Shown again in FIG.4 is the data stream 311 to be sampled including data packets 313, 315 and 317. Once again it is important to note that data stream 311 changes at points 308, 310, and 312 such that the data value in data packet 313 can be, and often is, different form the data value in data packet 315 or 317, i.e., the data value changes state from data packet 313 to data packet 315 and to data packet 317.

Also shown in FIG.4 is clock signal CLK 201. As is typical in the present state of the art, signal diagram 400 is for an "edge triggered" system.

Also shown in FIG.4 is first pulse signal 401 that includes first pulses 411, 413, and 415. In accordance with the present invention, first pulses 411, 413, and 415 are derived by the leading edges 324, 326 and 328 of clock pulses 323, 325, and 327 and are used to trigger a first pulsed latch (601 in FIG.6) to provide a transparency window equal to the pulse width 405 of first pulses 411, 413, and 415.

Likewise, according to the invention, a second pulse signal 403 includes second pulses 421, 423, and 425. In accordance with the present invention, second pulses 421, 423, and 425 are derived by the trailing edges 474, 476 and 478 of clock signal pulses 323, 325 and 327 and are used to trigger a second pulsed latch (603 in FIG.6) to provide a transparency window equal to the pulse width 407 of second pulses 421, 423, and 425.

Numerous methods for creating first pulse signal 401 and second pulse signal 403 are know to those of skill in the art. Consequently, the devices and

-14-

methods for creating first pulse signal 401 and second
pulse signal 403 are not discussed in detail herein to
avoid detracting form the present invention.

As shown in FIG.4, the clock skew tolerant
5   clocking scheme 400 of the invention, including first
pulse signal 401 and second pulse signal 403, shifts
the data sampling points from the leading edges 324,
326 and 328, and the respective data stream points 314,
316 and 318, to data sampling points 414, 416 and 418.
10   In addition, the separation windows 481, 483 and 485
are narrowed from a time equal to the entire pulse
width of clock pulses 323, 325 and 327, equal one-half
a clock cycle, to a time equal to the entire width of
clock pulses 323, 325 and 327 minus the pulse width 405
15   of a first pulse 411 and the pulse width 407 of a
second pulse 421.

In one embodiment of the invention, first pulse
width 405 is equal to second pulse width 407. In this
embodiment, separation windows 481, 483 and 485 are
20   equal to one-half a clock cycle minus the pulse width
405 or 407 of the first or second data pulse 411 or
421.

According to the present invention, the duration
or pulse width 405 of first pulses 411, 413 and 415 and
25   second pulses 421, 423 and 425 is determined by the
designer, with longer or larger pulse widths being more
tolerant of the max-time problem and the shorter or
smaller pulse width being more tolerant of the min-time
problem. In one embodiment of the invention, the pulse
30   widths 405, 407 of first and second pulses 411, 413 and
415 and 421, 423 and 425 are designed to be ten to
twenty-five percent of a clock cycle.

As noted above, FIG.4 shows one embodiment of the
clock skew tolerant clocking scheme 400 of the
35   invention employed with a typical synchronous data
circuit design operating as designed, with little or no
clock skew. Consequently, the effect of the clock skew

tolerant clocking scheme 400 of the invention in FIG.4
is minimal and the result is simply a narrowing of the
valid data windows. FIG.4 is included to show that the
clock skew tolerant clocking scheme 400 of the

5   invention can readily be employed with system where
there is little or no clock skew without interfering
with normal system operation. However, using clock
skew tolerant clocking scheme 400 of the invention, the
system is now more tolerate to potential clock skew

10 when, and if, it arises.

FIG.5 shows one embodiment of the clock skew
tolerant clocking scheme 500 of the invention when
employed to solve a max-time problem.

Shown in FIG.5 is the data stream 311 to be

15 sampled including data packets 302, 313, 315 and 317.
Once again it is important to note that data stream 311
changes at points 308, 310, and 312 such that the data
value in data packet 313 can be, and often is,
different form the data value in data packet 302, data

20 packet 315 or 317, i.e., the data value changes state
from data packet 302 to data packet 313 to data packet
315 and to data packet 317.

Also shown in FIG.5 is skewed clock signal CLKe
203. As discussed above, skewed clock signal CLKe 203

25 of FIG.3 and FIG.5 differs from clock signal CLK 201 of
FIG.3 and FIG.4 in that a leading "trigger" edge 354 of
clock pulse 353 is displaced or "skewed" early, or to
the left, with respect to leading edge 324 of clock
pulse 323 by skew time 350. Likewise, a leading

30 "trigger" edge 356 of clock pulse 355 is displaced or
"skewed" to the left with respect to leading edge 326
of clock pulse 325 by skew time 350. Likewise, a
leading "trigger" edge 358 of clock pulse 357 is
displaced or "skewed" to the left with respect to

35 leading edge 328 of clock pulse 327 by skew time 350.

As discussed above, the max-time problem arises
from the fact that because of skew time 350, leading

edge 354 of clock pulse 353 of skewed clock signal CLKe
203 would cause data stream 311 to be sampled at point
364 of data packet 302, instead of a point, such as
point 314, in the correct data packet 313.

5   Consequently, data packet 302 would be incorrectly
sampled instead of the correct data packet 313.
Therefore, since the value of data packet 313 can be,
and often is, different from the value of data packet
302, incorrect data would be sampled and used.

10   As shown in FIG.5, a similar situation results for
clock pulse 325 since, because of skew time 350,
leading edge 356 of clock pulse 355 of skewed CLKe 203
would cause data stream 311 to be sampled at point 366
of data packet 313, instead of a point, such as point

15   316, in the correct data packet 315. Consequently,
data packet 313 would be sampled instead of the correct
data packet 315. Therefore, since the value of data
packet 313 can be, and often is, different from the
value of data packet 315, incorrect data would be

20   sampled and used.

        Finally, as also shown in FIG.5, skew time 350,
would cause sampling at point 368 of data packet 315
instead of a point, such as point 318 in the correct
data packet 317. Consequently, data packet 315 would

25   be sampled incorrectly instead of the correct data
packet 317. Therefore, incorrect data would be
sampled and used.

        However, as also shown in FIG.5, according to the
invention, first pulse signal 501, that includes first

30   pulses 511, 513, and 515, corrects this max-time
problem. In accordance with the present invention,
first pulses 511, 513,and 515 are derived by the
leading edges 354, 356 and 358 of clock signal pulses
353, 355 and 357 and are used to trigger a first pulsed

35   latch (601 in FIG.6) to provide a transparency window
equal to the pulse width 505 of first pulses 511, 513,
and 515.

-17-

Likewise, according to the invention, a second pulse signal 503 includes second pulses 521, 523, and 525. In accordance with the present invention, second pulses 521, 523, and 525 are derived by the trailing

5   edges 574, 576 and 578 of clock signal pulses 353, 355 and 357 and are used to trigger a second pulsed latch (603 in FIG.6) to provide a transparency window equal to the pulse width 507 of second pulses 521, 523, and 525.

10   As shown in FIG.5, the clock skew tolerant clocking scheme 500 of the invention, including first pulse signal 501 and second pulse signal 503 shifts the data sampling points from data stream points 364, 366 and 368 to data stream points 314, 316 and 318,

15   respectively. Consequently, using the clock skew tolerant clocking scheme 500 of the invention, skew time 350 falls within the transparency window supplied by the pulse width 505 of first pulse 511 and data stream 311 is sampled point 314, in the correct data

20   packet 313. Likewise, skew time 350 falls within the transparency window supplied by the pulse width 505 of first pulse 513 and data stream 311 is sampled at point 316, in the correct data packet 315. Likewise, skew time 350 falls within the transparency window supplied

25   by the pulse width 505 of first pulse 515 and data stream 311 is sampled at point 318 in the correct data packet 317. Therefore, using the clock skew tolerant clocking scheme 500 of the invention, the max-time problem is solved.

30   In addition, the clock skew tolerant clocking scheme 500 of the invention creates separation windows 581, 583 and 585 between transparency windows and data sampling times are changed from time T4, T5 and T6 to times T1, T2 and T3, respectively.

35   In one embodiment of the invention, first pulse width 505 is equal to second pulse width 507. In this embodiment, the separation windows 581, 583 and 585 are

equal to one-half a clock cycle minus the pulse width (505, 507) of the first or second data pulse.

According to the present invention, the duration or pulse width 505 of first pulses 511, 513 and 515 and second pulses 521, 523 and 525 is determined by the designer, with longer, or larger, pulse widths being more tolerant of the max-time problem and the shorter, or smaller, pulse widths being more tolerant of the min-time problem. In one embodiment of the invention, the pulse widths 505, 507 of first and second pulses 511, 513 and 515 and 521, 523 and 525 are designed to be ten to twenty-five percent of a clock cycle.

As discussed above, in the prior art, one solution for the max-time problem was to simply slow down the clock signal frequency to the point that uncertainty in the clock arrival did not result in circuit failure. Obviously, slowing down the clock signal frequency had adverse effects on performance and was very undesirable. As shown above, the clock skew tolerant clocking scheme 500 of the invention solves the max-time problem without the need to slow down the clock signal frequency. Consequently, the clock skew tolerant clocking scheme 500 of the invention solves the max-time problem without adversely effecting system performance.

Also recall that another prior art solution to the max-time problem in latch-based designs was to employ "transparent" latches between stages. However, as also discussed below, this prior art solution to the max-time time problem failed to address the min-time problem and potentially made the min-time problem even worse. However, as shown in FIG.5, the clock skew tolerant clocking scheme 500 of the invention, including first pulse signal 501 and second pulse signal 503, provides that there is minimal opportunity for the first pulses 511, 513, and 515 to overlap with their corresponding second pulses 521, 523 and 525

since there is always a separation window 581, 583, and
585, equal to one-half a clock cycle minus the pulse
width of a first pulse between the trailing edge of a
first pulse 511, 513 and 515 and the leading edge of a
5   corresponding second pulse 521, 523 and 525,
respectively. Consequently, using the clock skew
tolerant clocking scheme 500 of the invention there is
minimal opportunity for the min-time problem to present
itself, i.e., using the clock skew tolerant clocking
10 scheme 500 of the invention, the min-time problem can
only present it self if the clock skew exceeds the
separation windows 581, 583, 585, equal to one-half a
clock cycle minus the pulse width of the first pulse
505. This would be an extreme and very rare level of
15 skew.

In addition, even in the rare circumstance where
there was such an extreme skew present, using the clock
skew tolerant clocking scheme 500 of the invention
including first pulse signal 501 and second pulse
20 signal 503, the min-time problem can, unlike in the
prior art, be solved by simply slowing down the clock
signal frequency since this will increase the
separation windows 581, 583 and 585.

FIG. 6 shows one embodiment of dual transparent
25 pulsed latches (601 and 603) operated by complementary
phases of the clock signal in accordance with one
embodiment of the invention. As shown in FIG.6, in one
embodiment of the invention, a first pulse latch 601
includes a first pulse generator 602 for producing a
30 first pulse, such as first pulses 411, 413 and 415 in
FIG.4 and 511, 513 and 515 in FIG.5, derived from the
rising edge of a clock pulse. Also shown in FIG. 6 is
a second pulse latch 603 including a second pulse
generator 604 for producing a second pulse, such as
35 second pulses 421, 423 and 425 in FIG.4 and 521, 523
and 525 in FIG.5, derived from the trailing edge of a
clock pulse. Logic block 611 is coupled between pulse

-20-

latches 601 and 603. Likewise, logic block 613 is coupled between second pulse latch 603 and third pulse latch 605. According to one embodiment of the invention, third pulse latch 605, like first pulse

5 latch 601, includes a first pulse generator 606 for producing a first pulse, such as first pulses 411, 413 and 415 in FIG.4 and 511, 513 and 515 in FIG.5, derived from the rising edge of a clock pulse.

Pulse latches and their operation are well known

10 to those of skill in the art. Consequently, the structure and methods of pulse latches is not discussed in more detail herein to avoid detracting from the present invention. For a more detailed discussion of pulse latches the reader is referred to virtually any

15 computer engineering text book. For example, "THE COMPUTER ENGINEERING HANDBOOK", edited by Vojin G. Oklobdzija, CRC press 2002, ISBN 0-8493-0885-1, see chapter 10.2 "LATCHES AND FLIP-FLOPS", authored by the present inventor, pages 10-35 to 10-52.

20 As shown in FIG.6, in one embodiment of the invention, the first and second pulses are generated locally by pulse generators 602, 604 and 606 and therefore, in one embodiment of the invention, the system remains a single-phase system and there is no

25 need to distribute additional signals widely.

As discussed above, according to the present invention, a clock skew tolerant clocking scheme addresses both the max-time and min-time problem by using dual transparent pulsed latches operated by

30 complementary phases of the clock signal. According to the present invention, a first pulsed latch is triggered by a first pulse derived by the leading edge of the clock signal pulse and the second pulsed latch is triggered by a second pulse derived from the

35 trailing edge of the clock signal. According to the present invention, the duration, or pulse width, of the first pulse and the second pulse is determined by the

-21-

designer with longer, or larger, pulse widths being more tolerant of the max-time problem and shorter, or smaller, pulse widths being more tolerant of the min-time problem.

5   By employing transparent pulse latches, the clock skew tolerant clocking scheme of the invention is max-time clock skew tolerant and the wider the transparent period is made, i.e., the larger the pulse width, the more clock skew can be hidden. In addition, the wider
10   the transparency period is made, the more time borrowing techniques can be employed.

Unlike the prior art latch-based solutions to the max-time problem discussed above, the clock skew tolerant clocking scheme of the invention is also
15   tolerant to min-time clocking skew problems as well. This is because, unlike prior art solutions, according to the invention, the transparency periods of the dual and complementary pulsed latches are always separated by a separation window and do not overlap and since the
20   transparency periods of the dual and complementary pulsed latches are non-over-lapping, there is almost never a transparency period between two successive stages and, therefore, there is no opportunity to introduce racing conditions.

25   In one embodiment of the invention, the pulse width of the first and second pulses is twenty percent of the clock cycle. Consequently, to a first order, the clock skew tolerant clocking scheme of the invention can tolerate thirty percent (fifty percent of
30   a clock cycle minus the twenty percent pulse width) of clock cycle skew without a min-time failure.

In addition, since, according to the invention, the first pulsed latch is triggered by a first pulse derived by the leading edge of the clock signal pulse
35   and the second pulsed latch is triggered by a second pulse derived from the trailing edge of the clock signal, the min-time clock skew tolerance can be

increased by changing the clock frequency since min-time skew tolerance, using the clock skew tolerant clocking scheme of the invention is determined by the clock cycle time divided by twice the pulse width of

5   either the first and second pulses. Consequently, unlike prior art schemes where the min-time problem was frequency independent, using the clock skew tolerant clocking scheme of the invention, both the max-time and the min-time problems can be solved by adjusting the

10   clock frequency. This feature of the clock skew tolerant clocking scheme of the invention is particularly advantageous during the system debugging phase of the design process since padding and margining for min-time is not required using clock skew tolerant

15   clocking scheme of the invention.

In addition, in one embodiment of the invention, the first and second pulses are generated locally by pulse generators and therefore, in one embodiment of the invention, the system remains a single-phase system

20   and there is no need to distribute additional signals widely.

The foregoing description of an implementation of the invention has been presented for purposes of illustration and description only, and therefore is not

25   exhaustive and does not limit the invention to the precise form disclosed. Modifications and variations are possible in light of the above teachings or may be acquired from practicing the invention.

Consequently, the scope of the invention is

30   defined by the claims and their equivalents.